


The INVERTER RANGE

PURE SINE CONVERTERS



PURE SINE

Pure Sine signal suitable for use with sensitive and demanding equipment




AUTOMATIC

Automatically switches to 220V mains power when plugged in



AUTO WATCH

With automatic restart



ERGONOMICS

As well as being silent, it is optimised for weight and volume.

EZA PUR-SINUS CONVERTERS ARE SPECIALLY DESIGNED AND ADAPTED TO THE SPECIFIC NEEDS OF LEISURE VEHICLES.

Operating in complete safety, they are capable of absorbing high currents and withstanding variations in load during use. Their current quality is equal to or better than that of a household socket.

It is intended for use with inductive electrical appliances (DIY equipment, pumps, motors, refrigerators, compressors, neon lights, etc.), appliances incorporating electronics sensitive to perfect current quality (refrigerators, freezers, microwaves, computers, washing machines, TVs, medical equipment, smartphone chargers and electrically-assisted bicycles) and/or appliances requiring high starting power (air conditioners, espresso coffee makers, hairdryers, DIY equipment, drills, etc.).

INTELLIGENT

Thanks to the MPS system (Mains Priority Function), the 1000, 2000 and 3000W inverters switch automatically when the vehicle is connected to the 220V mains (e.g. at a car park, campsite, at home, etc.) to save the auxiliary battery. When the vehicle disconnects from the mains, the inverter switches back to the battery in a few milliseconds to continue supplying the electrical consumer. Included: Low-voltage safety device to protect batteries against deep discharge, specific Recreational Vehicle wiring supplied and USB output throughout the range. Electronic protection against reverse polarity, short-circuit and overheating.


COMPATIBILITY

Compatible with all battery types, including Lithium LiFePo4. Wired remote control included (except for 300W model) for remote control and shutdown of the inverter to avoid draining the battery even when no consumer appliance is connected to the inverter. Reinforced mounting brackets for floor or wall installation. Appropriate cables for safe use and installation.



The INVERTER RANGE

PURE SINE CONVERTERS

PRODUCT FEATURES	300W	500W	1000W	2000W	3000W
	466376	466386	466390	466394	466398
RATED POWER	300W	500W	1000W	2000W	3000W
PEAK POWER (3sec.)	600W	1000W	2000W	4000W	6000W
TECHNOLOGY	PURE SINUSOIDAL WAVE				
INPUT VOLTAGE DC	11-16V				
OUTPUT VOLTAGE AC	230V - 50Hz				
AC SOCKET 	SCHUKO				
NO-LOAD CONSUMPTION	<0.60A	<0.60A	<0.80A	<0.95A	<1.3A
PRIORITY MPS SECTOR	YES				
LOW VOLTAGE SAFETY	YES, 11V				
HIGH VOLTAGE SAFETY	YES, 16V				
REVERSE POLARITY SAFETY DEVICE	YES				
SHORT-CIRCUIT PROTECTION	YES				
OVERHEATING PROTECTION	YES				
USB SOCKET OUTPUT	YES / 1USB 5V,2.1A				
MODE OF COMMUNICATION	-	LED REMOTE WIRED CONTROLLER (5M)			
AUTHORISED POSITION/FIXING	Horizontal and vertical				
AC CONNECTICAL	-	-	230V cable supplied / 1m		
DC CONNECTICAL	Cables supplied 6mm ² /50cmx3	Cables supplied 10mm ² /50cm x 2	Cables supplied 16mm ² /50cm x 2	Cables supplied 25mm ² /50cm x 2	Cables supplied 35mm ² /50cm x 2
PROTECTION FUSE	YES, EXTERNAL				
DIMENSIONS IN MM PRODUCT (L x W x H)	230*150*70	260*150*70	400*150*70	440*220*90	500*220*150
NET WEIGHT	1,5KG	2KG	3KG	5KG	8KG
SUPPLIED WITH	INSTRUCTIONS + CABLES				
CERTIFICATIONS, APPROVALS	R10 + CE (EMC - LVD) + RoHS				
WARRANTY	2 YEARS				

LOGISTICS DATA	300W	500W	1000W	2000W	3000W
	466376	466386	466390	466394	466398
EAN CODE	3700628245544	3700628245582	3700628245629	3700628245667	3700628245704
CUSTOMS CODE	8504408590				
SUPPLIER ORIGIN	CHINA				
DIMENSIONS IN MM PACKAGED PRODUCT (L x W x H)	320*200*135	320*200*140	460*200*135	490*290*170	540*330*230
PACKAGING	COLOR GIFT BOX				
GROSS WEIGHT (KG)	2.3KG	3KG	4.25KG	7KG	11KG
QTY CARTON	1				
QTY / MASTER CARTON / GROSS WEIGHT	6 / 14KG	6 / 18KG	4 / 17KG	2 / 14KG	1 / 11KG
QTY PALLET / GROSS WEIGHT	168 / 267KG	168 / 351KG	112 / 351KG	68 / 355KG	42 / 351KG
QTY CT / 20	2615	2615	1955	1035	490
QTY CT / 40 HC	6350	6350	4750	2520	1190

To access to the digital version, scan this QR Code.



Need some advice ?
Contact the Hotline on **+44 1376 428 006**



All our products come with a
2 Year Warranty



More information on
www.eza.fr