

The POWER STATION RANGE

START-E 18000 POWER BANK



POWERFUL BOOSTER

Can start your engine up to 30 times




INTELLIGENCE

Identifies your device for optimised charging



ECO LAMP

3 LED lighting modes: lamp, strobe, SOS



POWER BANK

Can charge all your digital devices

WITH EZA'S START-E 18000, GET MAXIMUM PERFORMANCE IN MINI FORMAT!

This power bank will allow you to recharge all your mobile digital devices (tablet, smartphone) as well as boosting your engine battery in the event of starting problems. Its compact size means you can take it with you wherever you go. With its integrated LED light, the Start-E 18000 provides back-up lighting and emergency functions, including an intermittent flash to signal your presence.

SUPER-POWERED BOOSTER

Car starter booster with 900A peak power capable of starting most vehicles up to 30 times on a single charge. (petrol engines up to 6.0 L and diesel engines up to 4.5 L).

MULTI-DEVICE CHARGER

2 USB ports for charging all digital devices: smartphones, tablets. 1 12V/16V/19V output port for charging all computers using the sockets provided.

TORCH LAMP

The START-E18000 has an ultra-bright, energy-efficient LED light function with 3 modes: torch, strobe light and SOS function.

RAPID CHARGE

The START-E18000 charges in 3-5 hours using the two charging options. If charged using the car charger, the START-E18000 will charge at 9V / 2A, otherwise it will charge at 5V / 2A.

The POWER STATION RANGE

START-E 18000 POWER BANK

PRODUCT FEATURES	START-E 18000
	496143
TECHNOLOGY	Li-Ion
CAPACITY	18000 mAh
BMS INTEGRATED	YES
RATED VOLTAGE	12,8V in Booster
VACUUM SELF-CHARGING	<15%/YEAR
MAXIMUM CONTINUOUS DISCHARGE CURRENT	450A / engine start : up to 6 litres (petrol engine) / 4.5 litres (diesel engine)
MAXIMUM DISCHARGE CURRENT IN PIC (1 Sec.)	Booster : 900A
MAXIMUM RECOMMENDED LOAD CURRENT	9V - 2A
CHARGING TIME ON AC-220V	9H
OPERATING TEMPERATURE AT DISCHARGE	-20°C / +60°C
OPERATING TEMPERATURE UNDER LOAD	0°C / +60°C
MODE OF COMMUNICATION	LCD SCREEN
SOLAR REGULATOR MPPT	NO
Input port	1 input 9V / 2A
Output port	1 x 12V output: start-up function with booster clamps 1 output 5V/2.1A 2 USB ports 12V/16V/19V for computer charging 1 function Lighting with LED lamp
PARALLELING	NO
ASSEMBLY IN SERIES	NO
HOUSING TYPE	PLASTICS
NUMBER OF CYCLES	800 CYCLES*
DIMENSIONS IN MM PRODUCT (L x W x H)	190*83*34
NET WEIGHT	0,600kG
SUPPLIED WITH	220v Charger, Cigar Lighter Cord, Carrying Case, Booster Clamps, Computer, Tablet and Smartphone Charging Connectors
CERTIFICATIONS, APPROVALS	CE/MSDS/UN38.3 R10 environment compatible
WARRANTY	2 YEARS



LOGISTICS DATA	START-E 18000
	496143
EAN CODE	6971268990041
CUSTOMS CODE	8507600090
SUPPLIER ORIGIN	CHINA
DIMENSIONS IN MM PACKAGED PRODUCT (L x W x H)	300 x 235 x 75
PACKAGING	COLOR GIFT BOX
GROSS WEIGHT (KG)	1,6KG
QTY CARTON	1
QTY / MASTER CARTON / GROSS WEIGHT	10 / 6,5KG
QTY CT /20	5000
QTY CT / 40 HC	12000



To access to the digital version, scan this QR Code.



Need some advice ?

Contact the Hotline on **+44 1376 428 006**



All our products come with a **2 Year Warranty**



More information on **www.eza.fr**